

**Iskra Avtoelektrika d.d.**

5290 Šempeter pri Gorici

Polje 15, Slovenia

**Tel:** +3865 33 93 000

**Fax:** +3865 33 93 801

**URL:** www.iskra-ae.com

## Switches – our product range

Type ARD	Rated voltage (V)	Nominal current (A)	Maximum permanent current (A)	Short-time maximum current (A)	Minimum cut-in voltage (V)	Consumption of current U=Un (A)	Mass (g)
<b>12 V</b>							
ARD 12 V 80 A	<b>12</b>	<b>80</b>	<b>≤80</b>	<b>350</b>	<b>≤8.4</b>	<b>2.8 ±0.1</b>	<b>695</b>
ARD 12 V 150 A	<b>12</b>	<b>150</b>	<b>≤150</b>	<b>350</b>	<b>≤8.4</b>	<b>2.8 ±0.1</b>	<b>695</b>
ARD 12 V 300 A	<b>12</b>	<b>300</b>	<b>≤300</b>	<b>500</b>	<b>≤8.4</b>	<b>≤3</b>	<b>1200</b>
<b>24 V</b>							
ARD 24 V 80 A	<b>24</b>	<b>80</b>	<b>≤80</b>	<b>350</b>	<b>≤16.8</b>	<b>1.1 ±0.1</b>	<b>695</b>
ARD 24 V 150 A	<b>24</b>	<b>150</b>	<b>≤150</b>	<b>350</b>	<b>≤16.8</b>	<b>1.1 ±0.1</b>	<b>695</b>
ARD 24 V 300 A	<b>24</b>	<b>300</b>	<b>≤300</b>	<b>500</b>	<b>≤16.8</b>	<b>≤2</b>	<b>1200</b>
<b>36 V</b>							
ARD 36 V 60 A	<b>36</b>	<b>60</b>	<b>≤60</b>	<b>200</b>	<b>≤25.5</b>	<b>≤0.8</b>	<b>695</b>
ARD 36 V 100 A	<b>36</b>	<b>100</b>	<b>≤100</b>	<b>350</b>	<b>≤25.5</b>	<b>≤0.8</b>	<b>695</b>
<b>48 V</b>							
ARD 48 V 60 A	<b>48</b>	<b>60</b>	<b>≤60</b>	<b>200</b>	<b>≤33.6</b>	<b>≤0.7</b>	<b>695</b>

For additional information on our products, please contact Iskra Avtoelektrika d.d.